

YET2133 REMOTE CONTROL MANUAL

一、Features:

- (1) Compatible brands: You can set it as a brand in the list through key operation;
- (2) Back-check function: You can check the brand of the current remote control through key operation;
- (3) Frequency: 240-930MHz;
- (4) Support: FSK, GFSK, OOK modulation



二、How to Work?

1.Brands back-checking

Press ① and ② together, and then hold ①, press ② three(3) times ,the Red LED will flash four (4) times, and the current remote control' s brands number is represented by the number of flashes each time. For example, if the brands button number is 1412, the LED will 1-4-1-2 flashes (the first time 1 flash, and the second time 4 flashes, the third time 1 flash, and the fourth times 2 flashes)

2.Brands setting

a. Press ① and ② together, and then hold ①, press the ② 4 times or more t, the LED will turn to a steady green color.

Press the button number in order according to the brands list to set a new brand remote control .For example: Press the 1-4-1-2 buttons in order, it is success when the LED flashes 3 times slowly.

b. After brands checking, and the LED turns to a steady green, you can reset the serial brand number for a new brand.

Press the button number in order according to the brands list to set a new brand remote control .

Noted:

- 1.If Green LED flashes quickly five(5) times and turn off, or there is no any operation within 10s, please do above process again.
2. If the button number exceeds out of the list below , the gGreen LED flashes quickly five (5) times and turn off, indicates that the setting failed, and the remote control retains the last brand setting value.

三、brands compatible list

number	Brand (specific model)	button number	Frequency (Mhz)	Modulation mode	Effective button	Remote control type
1	BENINCA (TO.GO-WV)	1111	433.92	OOK	①②	Rolling code
2	DOORHAN (TRANSMIT TER4)	1112	433.92	OOK	①②③④	Rolling code
3	KEY (PLAY)	1113	433.92	OOK	①②③④	Rolling code
4	GBD	1114	433.92	OOK	①②③④	Rolling code
5	NICE(NICE Flor-s)	1121	433.92	OOK	①②③④	Rolling code
6	DEA	1122	433.92	OOK	①②③④	Rolling code
7	PECCinin	1123	433.92	OOK	①②③④	Rolling code
8	FADINI	1124	433.92	OOK	①②	Rolling code
9	EQUO	1131	433.92	OOK	①②③④	Rolling code
10	Sommer	1132	433.92	FSK	①②③④	Rolling code
11	Sommer	1133	868.88	FSK	①②③④	Rolling code
12	HORMAN (EcoStarRSC2-433)	1134	433.92	OOK	①②	Rolling code
13	V2	1141	433.92	OOK	①②③④	Rolling code
14	ATA(PTX-4)	1142	433.92	OOK	①②③④	Rolling code
15	Motorline	1143	433.92	OOK	①②③④	Rolling code
16	Motorline	1144	868.35	OOK	①②③④	Rolling code

number	Brand (specific model)	button number	Frequency (Mhz)	Modulation mode	Effective button	Remote control type
17	centurion (NOVA)	1211	433.92	OOK	①	Rolling code
18	HiLand	1212	433.92	OOK	①②③④	Rolling code
19	FAAC(XT4433RC&XT2433RC/XT4868RC&XT2868RC)	1213	433.92	OOK	①②③④	Rolling code
20	FAAC(XT4433RC&XT2433RC/XT4868RC&XT2868RC)	1214	868.35	OOK	①②③④	Rolling code
21	YET	1221	433.92	OOK	①②③④	Rolling code
22	BFT (Type:BRCB)	1222	433.92	OOK	①②③④	Rolling code
23	Alutech (AT-4)	1223	433.92	OOK	①②③④	Rolling code
24	NICE(NICE SMLIO)	1224	433.92	OOK	①②③④	Rolling code
25	AUSTDOOR	1231	315	OOK	①②③④	Rolling code
26	F9	1232	365	OOK	①②③④	Rolling code
27	6225 V6	1233	365	OOK	①②③④	Rolling code
28	YS-1895R	1234	336	OOK	①②③④	Rolling code
29	YH-1A2	1241	315	OOK	①②③④	Rolling code
30	YH-1B2	1242	315	OOK	①②③④	Rolling code
31	HY-26LLC	1243	346.5	OOK	①②③④	Rolling code
32	JS-N23AA	1244	336	OOK	①②③④	Rolling code
33	SJ-2010	1311	433.92	OOK	①②③④	Rolling code
34	HD-08/JS-909B	1312	365	OOK	①②③④	Rolling code
35	YH/JS979-A2	1313	433.92	OOK	①②③④	Rolling code
36	HS/ JS979-AA	1314	365	OOK	①②③④	Rolling code
37	TY/ JS979-AA	1321	365	OOK	①②③④	Rolling code
38	Zhongtian	1322	433.92	OOK	①②③④	Rolling code

number	Brand (specific model)	button number	Frequency (Mhz)	Modulation mode	Effective button	Remote control type
39	Splett	1323	433.92	OOK	①②	Rolling code
40	Rima	1324	433.92	OOK	①②③④	Rolling code
41	Seaside	1331	433.92	OOK	①②	Rolling code
42	Doorman	1332	433.92	OOK	①②③④	Rolling code
43	Cap	1333	433.92	OOK	①②	Rolling code
44	Somfy	1334	433.92	OOK	①②③	Rolling code
45	Liftmaster	1341	315	OOK	①②③④	Rolling code
46	Liftmaster	1342	390	OOK	①②③④	Rolling code
47	Doorhan Pro (trnamsitter 2 pro)	1343	433.92	OOK	①②	Rolling code
48	Merlin	1344	433.92	FSK	①②③④	Rolling code
49	Rossi	1411	433.92	OOK	①②③④	Rolling code
50	HS1527	1412	433.92	OOK	①②③④	Learning code
51	HS1527	1413	315	OOK	①②③④	Learning code
52	HS1527	1414	330	OOK	①②③④	Learning code
53	CAME(TOP-432NA)	1421	433.92	OOK	①②	Fixed code
54	CAME(TOP-432EE)	1422	433.92	OOK	①②	Fixed code
55	CAME(TOP-432EV)	1423	433.92	OOK	①②	Fixed code
56	ParksonT18	1424	433.92	OOK	①②③④	Fixed code
57	Oceston	1431	433.92	OOK	①②③④	Fixed code
58	Omark	1432	433.92	OOK	①②③④	Fixed code
59	Oko (AC116-05)	1433	433.92	OOK	①②③④	Fixed code
60	DOOYA	1434	433.92	OOK	①②③	Fixed code